


**BOSCH**

Invented for life

# D263 Series Photoelectric Smoke and Smoke and Heat Detectors



- ▶ 12 V or 24 V input
- ▶ Designed for commercial or residential use
- ▶ Two-wire application
- ▶ Light-emitting diodes (LEDs) indicate the status of the chamber, power, and alarm
- ▶ Removable terminal block to simplify wiring connections
- ▶ Cable connection point for voltmeter sensitivity test
- ▶ Trim Plate TP280 for retrofit and remodeling purposes

The D263 Series includes the following detector models:

Model	Description
D263	Two-wire
D263TH	Two-wire with 135°F (57°C) heat sensor
D263THC	Two-wire with 135°F (57°C) heat sensor and auxiliary relay
D263THS*	Two-wire with 135°F (57°C) heat sensor and sounder

\* Sounders produce 85 dB at 10 ft (3 m).

Each of the D263 Series Detector models is UL Listed and works with commercial fire protective signaling and household fire warning systems. Each model detects smoke particles produced during wood, paper, and fabric combustion.

## System Overview

The D263 Series Detector models use an infrared (IR) LED light source and a silicon photodiode to measure light in a chamber. A fine screen covers the chamber to deter insects and to reduce dust accumulation and nuisance alarms.

During a fire, smoke particles reflect light onto the photodiode. When the photodiode measurements exceed the alarm threshold, the detector signals an alarm condition. After the alarm condition clears, interrupt power at the control panel to reset the detector.

Use a D132B Reversing Relay Module to activate the sounder (85 dB at 10 ft [3 m]). When using a D132B, the LED does not latch on alarm.

## Functions

### Chamber Calibration Tests

Check the sensitivity and calibration of any D263 Series Detector model using a visual check, a magnet test, or a voltage measurement test.

### Visual check:

When the detector's calibration is within the factory-listed range, the red alarm LED flashes once every 3.5 sec.

If the detector's calibration is out of range for more than 24 h, the red alarm LED flashes once a second.

### Magnet test:

Hold a magnet horizontally against the detector for about 10 sec and observe the LED.

- If the detector is within the factory-listed calibration range, it goes into alarm and the Alarm LED latches on.
- If the detector is too sensitive, the LED rapidly flashes six times (once every half second) and the detector goes into alarm.
- If the detector is not sensitive enough, the LED slowly flashes four times, once every 2 seconds, and the detector goes into alarm.

- If the detector does not operate, it does not signal an alarm.

**Voltage measurement test:**

Use a D1005 Test Cable and a digital voltmeter to measure the voltage and compare the results with the factory-listed sensitivity range.

**Certifications and Approvals**

Region	Certification	
USA	UL	UROX: Smoke - Automatic Fire Detectors (UL268 and A), UROX7: Smoke - Automatic Fire Detectors Certified for Canada (cULus),
	CSFM	7272-1615: 134
	NYC-MEA	274-93-E, Vol. VII
	MSFM	
Hong Kong	HKFSD	D263THC only D263THS only

**Installation/Configuration Notes**

Use smoke detectors for detection circuits that protect people. Use heat detectors for circuits that protect property.

**Compatible Products**

The following products are compatible with the D263 Series detectors:

Category	Product ID	Product Description
Control Panels		Bosch Security Systems makes no claim written, oral, or implied that the D263 Series detectors work with any two-wire control panels except those specified in the Control Panel Compatibility chart in <i>Technical Service Note</i> (P/N: 31866).
Modules	D132B	Reversing relay module

**Mounting**

The detector has a mounting plate that attaches on a standard four-inch back box.

For commercial and industrial installations in accordance with NFPA 72, space each detector 30 ft (9.2 m) apart.

**Wiring**

The terminal block accepts up to 12 AWG (2.3 mm) wire. You can remove the terminal block from the detector for easier wiring. The terminal block snaps in and out of the detector.

**Technical Specifications**

**Environmental Considerations**

Radio Frequency Interference (RFI) Immunity:	No alarm on critical frequencies in the range of 26 MHz to 950 MHz.
Relative Humidity:	Up to 93%, non-condensing
Temperature (operating):	+32°F to +120°F (0°C to +40°C)

**Mechanical Properties**

Dimensions (Diameter x H):	5 in. x 2 in. (12.7 cm x 5.1 cm)
Material:	High impact, fire retardant ABS plastic

**Relay Contacts**

Auxiliary	Form C: 1 A, 120 VAC/30 VDC at 1 A, 30 W maximum
-----------	---

**Power Requirements**

Current Draw (alarm):	Determined by control panel
Current Draw (standby):	0.080 mA at 12 V, 0.1 mA maximum
Current Draw (start-up):	0.12 mA
Current Draw (trouble):	0.1 mA maximum
Power-up Time:	22 sec maximum
RMS Ripple (maximum):	25% of DC input
Voltage (stand-by):	8.5 VDC to 33 VDC

**Ordering Information**

<b>D263 Two-Wire Smoke Detector</b> Two-wire photoelectric smoke detector.	<b>D263</b>
<b>D263TH Two-Wire Smoke/Heat Detector</b> Two-wire photoelectric smoke detector with a 135°F (57°C) heat sensor.	<b>D263TH</b>
<b>D263THC Two-Wire Smoke/Heat Detector with Auxiliary Relay</b> Two-wire photoelectric smoke detector with a 135°F (57°C) heat sensor and an auxiliary relay.	<b>D263THC</b>
<b>D263THS Two-Wire Smoke/Heat Detector with Sounder</b> Two-wire photoelectric smoke detector with a 135°F (57°C) heat sensor and a sounder.	<b>D263THS</b>
<b>D1005 Test Cable</b> Connects a digital voltmeter to the detector's calibration pin for verifying that the detector is within its calibration range	<b>D1005</b>
<b>DT-2 Detector Removal Tool</b> Use the DT-2 to remove, replace, or test the detector head	<b>DT-2</b>
<b>TP280 Trim Plate</b> For retrofit and remodeling purposes; 16.2 cm (6 in.) diameter	<b>TP280</b>



**Americas:**  
Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: +31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6258 5511  
Fax: +65 6571 2698  
apr.securitysystems@bosch.com  
www.boschsecurity.com

**Represented by**